



MASTECH MY68N Digital Multimeter

Digital multimeter measures AC/DC current and voltage, resistance, capacitance, frequency and tests continuity and diodes.

Features

- Functions:
 - AC/DC current and voltage
 - resistance
 - capacitance
 - frequency
 - continuity test (with buzzer)
 - diode test
- Data Hold function
- SMT application
- Automatic power off function after 40 min standstill
- Auto ranging
- Low battery indicator

Specifications

Display	3¾ digit LCD
DC voltage, V	400mV/4V/40V/400V±0.7%, 1000V±0.8% 400mV±3.0%
AC voltage, V	4V/40V/400V±0.8% 750V±1.0%
DC current, A	400µA/4000µA/40mA/400mA±1.2% 10A±2.0%
AC current, A	400µA/4000µA/40mA/400mA±1.5% 10A±3.0%
Resistance, Ω	400Ω/4kΩ/40kΩ/400kΩ/4MΩ ±1.2% 40MΩ ±2.0%
Capacitance, F	4nF±5.0%, 40nF/400nF/4µF/40µF/200µF±3.0%
Frequency, Hz	10Hz/100Hz/1000Hz/10kHz/200kHz ±2.0%
Continuity test	buzzer sounds if R <50Ω
Standards	IEC1010-1: CAT III 600V and CAT II 1000V
Power Supply	9V 6F22 × 1
Dimensions, mm	91 × 189 × 31,5



Package contains: Multimeter MY68N, test leads, protection case, manual